


BABUS 6

design: Roberto Mantovani




Supply current
 Courant d'alimentation
 Corriente de alimentación
500mA (V_f 8.7V)

Power
 Pouissance
 Potencia
4.5W



Photometric diagrams



CCT	Flux	CRI
2700K	421 lm	98+
3000K	446 lm	98+
3500K	464 lm	98+
4000K	482 lm	98+

Code Construction

Construction du code produit
 Construcción del código de producto

BT2 | X | XX | X | E |


BT2	X	Beam angle	XX	Color Temp.	X	Finishing	E
		Angle de faisceau Ángulo del haz		Température couleur Temperatura de color		Finitions Acabados	
	1	25°		27		B	
	2	45°		30		G	
				35		N	
				40		K	
				CU			

Drivers

Alimentateurs
 Alimentadores

Series wiring

Câblage en série
 Cableado en serie



0-10V

FLEXA-60-PRO-CC-10V

Programmable 60W CC 0-10V Dimming
 Dimming Range: 0.1%
Min. 1/Max. 6 Fixtures per Driver

Phase

FLEXA-12-500-CC-ELV

12W 500mA Constant Current
 Dimming Range: 10%
Min. 1/Max. 2 Fixtures per Driver

FLEXA-23-500-CC-ELV

23W 500mA Constant Current
 Dimming Range: 10%
Min. 3/Max. 5 Fixtures per Driver

Lutron 2-Wire Phase

Hi-Lume 2-Wire Phase / 500mA Constant Current / Dimming Range: 1%

LTEA.1

Min. 1/Max. 2
 Fixtures per Driver

LTEA.2

Min. 2/Max. 4
 Fixtures per Driver

LTEA.3

Min. 4/Max. 6
 Fixtures per Driver

Lutron Ecosystem

LDE.1


Hi-Lume Ecosystem
 500mA Constant Current
 Dimming Range: 1%
Min. 2/Max. 3 Fixtures per Driver

LDE.2

Hi-Lume Ecosystem Premier
 500mA Constant Current
 Dimming Range: 1%
Min. 4/Max. 5 Fixtures per Driver

MP-R040


Mounting Plate
 with 40mm Hole



T-BAR Installation

RO1040

Mounting Plate
 with 40mm Hole




IC Housings

IC064R01040

Recessed Box for
 Insulated Ceiling with
 40mm Hole

AT064R01040


Air Tight Recessed Box
 for Insulated Ceiling with
 40mm Hole



Optionals - Accessoires - Accesorios

CSBU01

Recessing box
 Boîtier d'encastrement
 Caja de empotrar



L001

Low luminance louvre
 Filtre basse luminance
 Filtro de baja luminancia



Note: the filter must be ordered together with the lighting fixture
Note: le filtre doit être commandé en même temps que l'appareil
Nota: el filtro debe pedirse junto con la luminaria